


Trendnet TEW-658BRM

Please follow the below steps to configure Trendnet TEW-658BRM modem


- Establish a connection between the device and the router via network cable or Wi-Fi (if there's a WIFI password you have to check bottom of the router. If you turn the router over, you should see a sticker, and one of the pieces of information should say something like "Wi-Fi Password" or "WPA passcode.")
- Open a browser and type 192.168.10.1 in the address bar




- You will be prompted to enter Username: admin and Password: admin



- After logging in Click Setup Wizard and Select PVC0 then click Next



- Under Internet Settings , Select PPPoE (RFC-2516 PPP over Ethernet) then click Next



- Choose Manual Selection as Connection Method then click Next

SETUP WIZARD	WELCOME TO SETUP WIZARD
SETUP	The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.
ADVANCED	DETERMINE CONNECTION METHOD SELECT
MAINTENANCE	<input type="radio"/> Auto-detect
STATUS	<input checked="" type="radio"/> Manual Selection
HELP	<input type="button" value="Back"/> <input type="button" value="Next"/> <input type="button" value="Cancel"/>
LOGOUT	

- Make Sure Auto PVC is disabled then type VPI and VCI , VPI should be 0 in case DSP is Ogero and 8 in case DSP is GDS while VCI should be 35
- Choose LLC as Encapsulation then click Next

SETUP WIZARD	WELCOME TO SETUP WIZARD
SETUP	The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.
ADVANCED	INTERNET CONNECTION SETTINGS
MAINTENANCE	Enable AutoPVC <input type="button" value="Disable"/>
STATUS	VPI <input type="text" value="8"/> (0~255)
HELP	VCI <input type="text" value="35"/> (32~65535)
LOGOUT	Encapsulation <input type="button" value="LLC"/>
	ATMQoS <input type="button" value="UBR"/>
	Peak Cell Rate <input type="text" value="6000"/> (0~6000 cells/s)
	Enable Default Vlan <input type="button" value="Disable"/>
	PPPoE PassThrough <input type="button" value="Enable"/>
	<input type="button" value="Back"/> <input type="button" value="Next"/> <input type="button" value="Cancel"/>

- In PPPoE page type Username and Password of ADSL account
- Keep other default settings unchanged then click Next

TRENDNET 300Mbps Wireless N ADSL 2/2+

SETUP WIZARD

WELCOME TO SETUP WIZARD
The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.

PPPOE

State of Connection: Enable
IP Mode of Connection: Dynamic
Name: pppoe
NAT: Enable

User Name: D??????@idm.net.lb
User Password: [masked]
Confirm Password: [masked]

Max MRU: 1492 (576~1492)
DNS Enabled: Enable
DNS Override Allowed: Disable
DNS Server 1: [optional]
DNS Server 2: [optional]
PPPoE Service Name: [optional]

MAC Address: 00 : E0 : 4C : 81 : 86 : 82 [Clone MAC]
PPPoE AC Name: [optional]
Connection Trigger: AlwaysOn
Idle Disconnect Time: 0 (30~3600 seconds)
LCP Interval: 20 (0~86400 seconds)
Proxy ARP Enable: [unchecked]

Back Next Cancel

- Under Wireless basic settings type Wireless Name In SSID Textbox then click Next

SETUP WIZARD	WELCOME TO SETUP WIZARD
SETUP	The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.
ADVANCED	WIRELESS BASIC SETTING
MAINTENANCE	Device Name wlan0
STATUS	Device <input checked="" type="checkbox"/> Enable
HELP	SSID TRENDnet658
LOGOUT	BSSID 00:E0:4C:81:86:82
	Wireless Channel Auto
	Wireless Mode 802.11n + 802.11g + 802.11b
	Back Next Cancel

- Under Security Configuration Select WPA2 as Security Mode

SETUP WIZARD	WELCOME TO SETUP WIZARD
SETUP	The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.
ADVANCED	SECURITY CONFIGURATION
MAINTENANCE	Security Mode
STATUS	None
HELP	None
LOGOUT	WEP
	WPA
	WPA2
	WPA/WPA2+TKIP/AES
	Cancel

- Make sure Authentication type is PSK and Encryption type is TKIP or AES
- In Passphrase textbox type wireless password (safest passwords are long and contain at least 8 digits of mixed letters, and numbers)
- You will need to re-enter that same passphrase again in the space titled Confirmed Passphrase then click Next

TRENDNET 300Mbps Wireless N ADSL 2/2

SETUP WIZARD

WELCOME TO SETUP WIZARD
The step-by-step setup wizard will guide you through to configure your modem and connect to the Internet.

SETUP WIZARD

SETUP

ADVANCED

MAINTENANCE

STATUS

HELP

LOGOUT

SECURITY CONFIGURATION

Security Mode **WPA2**

Authentication Type PSK EAP

Encryption Type TKIP AES TKIP and AES

Group Rekey Time 86400 (seconds)

SECURITY ENCRYPTION(WEP)KEY

Encryption Strength 64bit

Key Format ASCII

Passphrase [Redacted] Generate

Key1

Key2

Key3

Key4

PASSPHRASE

Confirmed Passphrase trendnet

Back Next Cancel

- The following message will be displayed. Click on Ok to Save configuration and reboot your modem

