## Trendnet TEW-657BRM

- Establish a connection between the device and the router via network cable or Wi-Fi
- Open a browser and type 192.168.10.1 in the address bar



• You will be prompted to enter Username: admin and Password: admin

TEW-657BRM × +	
← → C (  http://192.168.10.1	
TRENDnet TEV	W-657BRM
USERNAME	(admin
PASSWORD	(admin )
LOG	
	4- a

- In the left pane, click on Wireless
- Type Wireless Name in SSID1 then click on Configure SSID1

	DNET	150Mbps Wireless N ADSL 2/2+ Modem Router TEW-657BRM
Setup Wizard	Wireless	
LAN		
10/2	Region	
VVireless	Region:	Asia 🗸
Password	Multi SSID	
Mode	SSID :	TRENDnet657 ✓         SSID1 (Service Set Identifier)
Status		Broadcast SSID     Isolation Within SSID
Advanced		Security Setting:
Administration	Options	SSID1 :Disabled Configure SSID1

- After clicking on configure SSID1 a popup window appears to configure wireless security
- Select WPA2-PSK as Security system and in PSK Textbox type wireless password (safest passwords are long and contain at least 8 digits of mixed letters, and numbers)
- Select TKIP as Encryption then click Save and Close popup window

less Security - Google Chrome				_		×	
trendnet.com/emulators/TEW-657BRM_V1.0R/w_wsec.htm						Q	
Wireless Security							
Security System WPA2-PSK							
PSK:				$\leq$			
Encryption: TKIP 🗸							
s	Save	Cancel					
4	$\triangle$			Help	Close		

• After closing popup window Scroll main page down to click Save

TREND:	IET	150Mbps Wireless N ADSL 2/2+ Modem Router TEW-657BRM
Setup Wizard LAN Wireless	Channel NO. Extension Channel. Isolation Between SSID WMM support	Down channel V
Password	Bandwidth: Mac Address Filter Allow access by:	20MHZ only
Status	WiFi Protect Setup	Trusted Wireless stations only     Set Stations
Administration	Enable WPS AP PIN Code:	✓ Regenerate
Log Out	Join Wireless Client WDS Setup	Input Client PIN Code: 12345670 OK
	Enable WDS MAC Address List	AP 1:
		Copyright © 2009 TRENDnet: All Rights Reserved.